# HYUNDA POWER EQUIPMENT

Diesel Generator Standby Power 66KVA 3 Phase 1500 rpm DHY65KE DHY65KSE



All Days | Safty | Reliable | Stability



# **TECHNICAL SPECIFICATION**

DHY65KE OPEN TYPE / DHY65KSE CANOPY TYPE

## **Benefits and Feature**

- > Use best quality vehicle engine, low fuel consumption, running reliable
- > Use high quality and performance brushless alternator, with AVR
- > High quality controller of COMAP/ DEEPSEA
- > Block design electrical control system, easy operate and maintenance

### **Technical Specification**

Prime Power	KVA/ KW	60/48
Standby Power	KVA/ KW	66/ 52.8
Power Factor		0.8
Frequency	Hz	50
Rate Voltage	V	400/230
Rate Current	А	95.27
Controller	С	OMAP/DEEPSEA
Control Voltage	DC / V	24
Battery Capacity	Ah	60x2
Coolant Capacity	L	18.8
Fuel Tank Capacity(Base frame)	L	160
Fuel Consumption	L/hour	16.13
Running Time	Hour	6.82

### > Standard 8 hours generator running base frame fuel tank (100% load)

- > With baseframe forklift hole and generator canopy lifting hole
- > Industrial waterproof canopy, ensure generator all days running

50Hz

Standby 66KVA

- > Industrial silencer (7 meters the noise is lower than 68 dB)
- > Easy operation, IP23 protection industrial sockets and plugs
- > Four pole circuit breaker with RCD earth protection
- > Standard ATS function connector

Voltage		
Steady state regulation	%	≤ ± 0.5
Dynamic voltage renewal	%	≤+20~-15
Stable time	Sec	2.0
Waveform distortion		≤3
Volatility		≤0.5
Frequency		
Steady state regulation	%	≤ ± 1
Dynamic frequency renewal	%	≤+10~-7
Stable time	Sec	≤3
Volatility		≤0.5
Environment require		
Temperature	С	≤40
Humidity	%	≤60
Altitude	m	≤1000
Standard		

ISO3046, ISO8528, ISO9001-2008

### Dimension | Weight | Sound



**OPEN TYPE** DHY65KE Length mm

Width (W)	mm	950
Height (H)	mm	1340
Weight net	Kg	1255
loading capacity (units/containe	r)	
Sound @7 meter	dB	90



## DHY65KSE CANOPY TYPE

Length	mm	2670
Width (W)	mm	1080
Height ( H )	mm	1450
Weight net	Kg	1400
loading capacity (units/container)		
Sound @7 meter	dB	68

## Note

1. Generator continuous running at variable load for unlimited periods with 10% overload available for 1 hour in any 12 hours period

2390

2. Every generator strictly test on 0%, 25%, 75%, 100%, 110% load dynamic responsiveness ability, and all protections



Powerful engine and reliable running quality Durable running performance and was proofed by vehicle's application

### **Compact structure**

Compact structure and metal materials saving for low cost

Low maintenance and repair cost Air,fuel and oil tubes are silicone and stainless steel materials, which reduce leakage problems substantially

Excellent start performance Fuel injector and pump were tested fully in Various environments, which provide excellent start and running performance

# **DIESEL ENGINE**

	Model		HY4DX23
	Prime power	Kw	57
	Structure		4 cylinder,inline
	Fuel type		Diesel
	Fuel consumption	L/Hour	16.13
	Lubricant consumption	L/Hour	0.08
	Governor		Electrical
	Coolling	-	Water
	Lubricant capacity	the second	13
	Air intake flow	m <sup>3</sup> /min	4.8
	Exhaust gas flow	m³/min	13.4
in the	Exhaust gas temperature	C	440
	Exhaust gas back pressure	e KPa	6.7
2	Compression ratio	2	17
	Aspiration T	urbocharg	ering intercooled
	Bore	mm	102
	Stroke		118
	Displacement		3.86
	SAE		3/11.5
	Dimension	mm	$870 \times 770 \times 680$
	Net weight	Kg	350

# **ALTERNATOR**

Model		224G48
Prime power	kVA	60
Structure		1 bearing
Excitation mode		Self-excitation
Insulation class	CALCULAR OF	Н
Protection class		IP23
TIF	6	<50
THE	and a	<2%
Air flow	m³/s	0.216
AVR Model		SX460



**Best structure** Excellent design ensures compact structure and perfect appearance

**Excellent performance** Excitation enhanced system improves start and short circuit's protection performance

Economy Less parts involved and the most market's demand lead to cheap price and fine quality

Easy maintenance and repair Core parts won't be involved in repair job, AVR can be replaced easily, examining diode doesn't disassemble rotor

# **CONTROL PANEL**

3

## Controller



## Comap AMF20

Support engine and alterantor monitoring, measurement and protection. This is long-running and back-up unit to integrate the best way to control, support Modbus standard, modem, RS485, USB and internet.

## Deepsea DSE6120



DSE6110/20 MKIII AUTO START & AUTO MAINS (UTILITY) FAILURE CONTROL MODULES

Measurement, displayment	
Genset prime power Kw	•
Power factor	•
Engine speed	•
Phase to neutral voltage	•
Phase to phase voltage	•
Genset frequency	•
Genset current	•
Mains Phase to neutral voltage	0
Mains Phase to phase voltage	0
Mains frequency	0
Engine oil pressure	•
Engine water temperature	•
Fuel level	
Battery voltage	•
Genset power KVA	•
Genset running time	•
Genset output KWh	•
	•
Alarm, shutdown function	
Low oil pressure warning, shutdown	•
High water temperature warning, shutdown	•
Engine over and under speed shutdown	•
Low fuel level warning, shutdown	•
Battery low and high voltage warning	•
Battery chargering failure	•
Genset low and high voltage warning, shut down	•
Alternator 3 phase voltage unbalance shut down	•
Alternator low and high frequency warning, shut down	•
Genset over load shutdown	•
Alternator 2 phase automation balance in the	•
Alternator 3 phase current unbalance shutdown	0
	~
Mains low and high voltage warning	0
Mains low and high voltage warning	
Mains low and high voltage warning Mains low and high frequency warning Optional	
Mains low and high voltage warning Mains low and high frequency warning Optional	0
Mains low and high voltage warning Mains low and high frequency warning Optional Remote start and stop	•
Mains low and high voltage warning Mains low and high frequency warning Optional Remote start and stop RS232 card USB card	• • ×
Mains low and high voltage warning Mains low and high frequency warning Optional Remote start and stop RS232 card USB card RS485 card	• ×
Mains low and high voltage warning Mains low and high frequency warning Optional Remote start and stop RS232 card USB card RS485 card Multi language display	<ul> <li>X</li> <li>X</li> </ul>



Electrical system

## Maintenance spare parts

